

**5600P24/1250**

MRA Low Power Remote Amplifier Power Supply

Installation Instructions

The 5600P24/1250 power supply suits the 560110R Low Power Remote Amplifier and supplies 24 V d.c. at 1.25 A. The power supply is used as needed to provide maximum audio output from the Low Power Remote Amplifier. The power supply is required for standalone amplifier operation when the amplifier is not connected to an MRA Matrix Switcher.

The power supply requires connection to a wall socket. Several international power adapters are included for use in locations worldwide. Select the appropriate adapter and fit it to the power supply body. The adapter slides into the power supply and you hear a definite click when it is fully engaged. To remove the adapter, press on the PUSH button and slide the adapter from the power supply.

Important Notes:

- The power supply is for indoor use only.
- Allow ventilation around the power supply.
- Do not allow liquids to drip or splash on the power supply.
- Disconnect the power supply from the amplifier when connecting speaker wires.
- If ambient operating temperatures are expected to be above 45° C, use the high temperature switch mode power supply.
- There are no user serviceable parts inside the power supply.



If you have any questions or concerns, please contact your nearest Clipsal Integrated Systems (CIS) or Schneider Electric technical support or sales representative.

Specifications	
Parameter	Description
Input voltage	100 to 240 V a.c.
Frequency range	50 to 60 Hz
Output voltage	24 V d.c.
Output current	1.25 A
Applicability	For use with Clipsal 560110R Audio Amplifier
Mfr's model number	PSC30R-240
Compliance	AS/NZS Safety Certificate, C-Tick, TUV/GS, cULus listed.
Device class	Class II LPS
Efficiency level	IV
Operating ambient temperature	0° C to 45° C
Dimensions	120mm x 61mm and extends 50 mm from wall outlet

There are no user serviceable parts inside the power supply.

Two-Year Warranty

The 5600P24/1250 MRA Low Power Remote Amplifier Power Supply carries a two-year warranty against manufacturing defects. For all warranty enquiries, contact your local Clipsal or Schneider Electric sales representative. The address and contact number of your nearest Schneider Electric office can be found at <http://www.clipsal.com>.